


AX1800 Whole Home Mesh Wi-Fi 6 Router



COVR-X1870 (2-PACK)



Cover your Whole Home in Seamless Mesh Wi-Fi



- Wi-Fi 6 technology provides faster speeds, greater capacity and less network congestion
- Next-generation speeds up to 1.8 Gbps (574 + 1200) built for the modern device-dense smart home
- Dual-band Wi-Fi makes 4K streaming, gaming and video chatting a breeze
- 4 Gigabit Ethernet LAN ports and 1 Gigabit Ethernet WAN port provide optional wired connectivity
- D-Link Wi-Fi Mesh lets you add other compatible D-Link Wi-Fi Mesh devices to expand your network as you wish
- BSS coloring helps organize data packets, making your network more efficient and improving overall Wi-Fi 6 performance
- Mesh Smart Roaming technology auto connects you to the strongest signal
- Voice Control for an even easier home Wi-Fi networking experience



 **Single Pack**
Coverage up to
275 sqm / 3000 sq. ft.

 **2-Pack** 
Coverage up to
510 sqm / 5500 sq. ft.

 **3-Pack** 
Coverage up to
740 sqm / 8000 sq. ft.

 **4-Pack** 
Coverage up to
925 sqm / 10000 sq. ft.



Wi-Fi 6 – Next Generation Wi-Fi

Designed for today's device-dense homes, the Covr AX Wi-Fi 6 solution is perfect for 4K streaming, VR gaming, video calling and keeping all your smart home devices connected.



Smart Roaming

Seamlessly connects your devices to the strongest signal as you move from room to room, eliminating the need for them to disconnect and reconnect.



OFDMA

Small data packets destined for multiple devices are transmitted together and never have to queue up again. Perfect for Smart Homes filled with bandwidth-hungry IoT devices battling for bandwidth.



Smart Steering

Automatically steers your devices to the optimal wireless band, ensuring you're always connected to fast, reliable Wi-Fi throughout your home.



Simple Setup

Covr Points come pre-paired out of the box, just plug them in and get started.



Profile-based Parental Controls

Assign devices to family members' profiles to individually block devices and websites, set schedules for access, and turn off Wi-Fi.



Expandable Network


Covr is a scalable solution. Add extra Covr Points where you need more coverage.



Works with your existing Router or Gateway

Simply connect Covr to the Router or Gateway provided by your ISP to add whole home coverage to your network.

Technical Specifications

Model	COVR-X1870 (2-Pack)
Product Image	
Coverage	510 sqm / 5500 sq. ft.
General	
Device Interfaces	1 x WPS Button, 4 x 10/100/1000 Mbps Gigabit Ethernet ports, 1 x 10/100/1000 Mbps Gigabit Ethernet WAN Port. 1 x Power Button, 1 x Power Connector
LED	Power/ Status
Antenna Type	2 x 2.4G WLAN Internal Antenna, 2 x 5G WLAN Internal Antenna
Wi-Fi Data Rate	2.4 GHz Up to 574 Mbps, 5 GHz Up to 1201 Mbps
Wireless IEEE Standard	IEEE 802.11ax/ac/n/g/b/k/v/a/h
WAN Interface	Static IP, Dynamic IP, PPPoE, PPTP, L2TP, DS-Lite, Support 802.1p & 802.1q VLAN tagging and Priority bit, Concurrent session: 30000
Functionality	
Security Protocol	WPA/WPA2 -Personal, WPA2-Personal, WPA2/WPA3 – Personal (WPS not supported), WPA3 Only (WPS Not supported)
Firewall	DoS, Stateful Packet Inspection, Anti-spoofing Checking, IP/MAC Address Filtering, 1 x DMZ
Mesh	D-Link EasyMesh
QoS	D-Link Intelligent QoS Technology
SpeedTest	Ookla SpeedTest
Software	
Device Management	D-Link Wi-Fi app (iOS and Android), Web UI
Voice Assistants	Amazon Alexa, the Google Assistant
Physical	
Hardware version	A1
Size	100 x 100 x 194 mm (3.94 x 3.94 x 7.64 in)
Weight	380 g (0.84 lbs)
Power Input	12 V 1A
Maximum Operating Voltage	12 V
Maximum Power Consumption	12 W
Operating Temperature	0 to 40 °C (32 to 104 °F)
Storage Temperature	-20 to 65 °C (-4 to 149 °F)
Operating Humidity	10% to 90% non-condensing
Storage Humidity	5% to 95% non-condensing
Certifications	CE , FCC , IC, RCM